



OWL TIMECLOCK



Owl Timeclock Code Blue

When Seconds Matter

- Count up, count down and optional wireless synchronized time modes
- Bright LED digits are viewable up to 160-feet
- Simple installation, low maintenance
- Battery back-up will keep time internally during count up/count down modes
- 1-year manufacturer's limited warranty

[Request Quote](#)

When seconds matter, count on Owl Timeclock's Code Blue digital clocks. The easy-to-use system counts up or counts down by seconds to monitor time in critical situations. Count up mode displays elapsed time. Count down mode displays time remaining. Upon reaching zero in count down mode, the clock flashes and counts negative time until stopped. A battery back up will keep time internally in the event of a power outage.

Owl Timeclock's Code Blue controller is easy to install and easy to operate. The digital clocks feature bright red or bright blue LED digits for high visibility. Clocks are available in two sizes, 2.5" or 4" with 6 digits, including the second indicator.



When not in timer mode, the digital clock can be used in conjunction with an Owl Timeclock Wireless System to provide accurate time synchronized with the rest of the facility. Owl Timeclock uses the proven industry standard of using frequency hopping technology to broadcast between the 902MHz and 928MHz radio frequencies. This delivers a dependable wireless synchronized clock signal for the medical market.



OWL TIMECLOCK

www.owltimeclock.ca

Head Office: **Toronto** 310 Judson St., Unit 6, Toronto, Ontario M8Z 5T6
Tel: 416-252-1186 Toll Free: 1-877-567-0633

Montreal
Tel: (514) 333-3273

Edmonton
Tel: (780) 438-2181

Calgary
Tel: (403) 258-2611

Vancouver
Tel: (604) 873-6571

Code Blue

TimeTraxsync

- Easy to operate in count up, count down or optional wireless time modes
- 6 digit timer will count up to 99:59:59 by seconds, and count down from 99:59:59 by seconds
- Unit will flash and display negative numbers when counting down past zero
- Time of day can be received via Owl Timeclock wireless transmitter or an Owl Timeclock wired solution
- Battery back-up will keep time internally when power is out for up to 7 days during the count up/down modes
- Wall mount controller uses standard electrical box and connects to digital clock using a RJ45 cable (included)
- Capable of receiving wireless RF synchronization signal every 20 seconds from Owl Timeclock's optional RF Transmitter when not in timer mode
- Clock face is tinted to reduce glare
- Durable ABS frame and shatterproof polycarbonate lens
- Extremely rigid body construction designed for durability and long life
- Available in red or blue digits
- 110-240 VAC (not battery operated)
- Tamper-proof mounting bracket (optional)
- Made in the USA

Warranty

1-year manufacturer's limited warranty with free product replacement



Item Description:
Code Blue Controller

Model #:
CBPLATEKIT

All code Blue digital clocks have black bezels, Select number, size and color (Red or Blue).

2.5" - 6 Digit Red LED, 100-240 VAC
4" - 6 Digit Red LED, 100-240 VAC
2.5" - 6 Digit Blue LED, 100-240 VAC
4" - 6 Digit Blue LED, 100-240 VAC

9D26BRCT
9D46BRCT
9D26BBCT
9D46BBCT

Specifications:

Item Weight:

2.5" - 6 Digit 1.5 lbs. (0.680kg)
4" - 6 Digit 2.3 lbs. (1.043kg)

Item Dimensions:

2.5" - 6 Digit 4.5"H x 11.12"W x 1.44" D
(11.43 cm x 28.24 cm x 3.65 cm)
4" - 6 Digit 6.15"H x 15.36"W x 1.44"D
(15.62 cm x 39.01 cm x 3.65 cm)

Voltage:

Universal 50/60Hz 100-240 VAC



www.owltimeclock.ca

Head Office: **Toronto** 310 Judson St., Unit 6, Toronto, Ontario M8Z 5T6
Tel: 416-252-1186 Toll Free: 1-877-567-0633

Montreal
Tel: (514) 333-3273

Edmonton
Tel: (780) 438-2181

Calgary
Tel: (403) 258-2611

Vancouver
Tel: (604) 873-6571